



HA351

Load break switch 3P 125A

Technical Features	
Electric current	
Rated current	125 A
Rated short-time withstand current lcw IEC 60947	7 kA
Acceptable current rating AC21	125 A
Acceptable current rating AC21 category A	125 A
Acceptable current rating AC21 category B	125 A
Acceptable current rating AC22 category A	125 A
Acceptable current rating AC22 category B	125 A
Acceptable current rating AC23 category A	125 A
Acceptable current rating AC23 category B	125 A
Rated short-circuit making capacity Icm under 415 V AC according to IEC 60947-3	11.90 kA
Rated short-time withstand current lcw 1s IEC 60947	7 kA
Architecture	
Number of poles	3
Control/operation element	Long rotary handle
Device construction type	Fixed built-in
Type of pole	3P
Dimensions	
Height	135 mm
Width	140 mm
Depth	120 mm
Cover, door	
Interlockable	Yes
Safety	
Ingress Protection (IP) class	IP00
Connection	
Cross-section rigid conductor	50 mm² max.
Cross-section flexible conductor	50 mm²
Voltage	_
Rated insulation voltage Ui	800 V
Rated impulse withstand voltage Uimp	8000 V
Rated operational voltage Ue	380 - 415 V
Power	
Power loss per pole at In	1.80 W
Total power loss under IN	5.40 W
Rated operational power under 400 V AC AC1	82000 W

W 82000 W Rated operational power under 400 V AC AC1 Rated operational power under 400 V AC AC23 56000 W

Controls and indicators	
Motor drive integrated	No
Use conditions	
Operating temperature	-20 - 70 °C

Frequency	50 - 60 Hz
Functions	
Is reversing switch	No
Version as emergency stop installation	No
Version as main switch	Yes
Version as maintenance/service switch	Yes

Frequency

Product Datasheet

HA351



Functions Version as safety switch Yes Version as switch disconnector compact Yes Equipment Motor drive optional No 0 Number of auxiliary contacts as change-over contact Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Installation, mounting Nominal tightening torque 9 - 9.9 Nm Sustainability Halogen free Yes REACh-SVHC free Yes RoHS conform Yes