Product Datasheet

TRE520



15 min



TRE520









Motion detector radio, with battery, IP55, white

Technical Features

-					
-1)	ım	en	SI	n	ns

Installation height	4 - 4 m
Recommended installation height	2.50 - 2.50 m

Settings

Supported configuration mode	ETS
	easy
	quicklink

Minimal duty cycle	30 9

Functions Maximal duty cycle

Connectivity	
With bus system KNX radio	Yes

Scope of delivery

ocope of delivery	
Bus connection included	Yes

Lighting

Response brightness adjustable	5 - 1000 lx

Detection

Detection angle	220 - 220
Detection angle horizontal	220 - 220

Use conditions

Operating temperature	-20 - 55 °C
-----------------------	-------------

Materials

Material	Acrylonitrile-Butadiene-Styrene (ABS)
	Polycarbonate (PC)

Texts

Function	Easy additional functions: +6 scenes, on/off operating mode, scene call-
	up upon motion/no motion
	Reset function (to factory setting)

Installation mode	For well and sailing manuating	corner installation with adapter
installation mode	For wall and celling mounting	, corner installation with adapter