

HED631H

### Moulded Case Circuit Breaker h630 4P 70kA 630A LSI

#### **Technical Features**

Electric comment

630 A
100 kA
100 kA
-

Rated ultimate short-circuit breaking capacity Icu under 400 V AC IEC 60947-2

70 kA

Rated ultimate short-circuit breaking capacity Icu under 415 V AC IEC 60947-2

70 kA

Breaking capacity on 1-pole for AC 230 V IEC 60947-2

60 kA

Breaking capacity on 1-pole for AC 400 V IEC 60947-2

9 kA

### Architecture

Number of poles	4
Control/operation element	Toggle
Device construction type	Fixed built-in

### Capacity

Number of modules	10.50
-------------------	-------

### Tripping

Response time when opening	10 ms

### **Settings**

Magnetic protection knob setting xIN	2.5
	5
	8
Range of magnetic adjustment	3500 A
	4410 A

	5600 A
	6300 A
Thermal protection knob setting xIN	0.4
	0.5
	0.62

	0.9 0.95
Adjustment range short-term delayed short-circuit release	0 - 0 A

## Frequency 50 - 60 Hz

# Installation, mounting Nominal tightening torque

Nominal tightening torque	22 - 22 Nm
Mounting-/Connection Position	Front

### Voltage

Frequency

Rated impulse withstand voltage Uimp	8000 V
Rated insulation voltage Ui	800 V
Rated operational voltage Ue	220 - 690 V

### Functions

Tri	unit	LSI

### Main electrical attributes

Magnetic protection trip time	00 -	- 200	1 O	m	S
-------------------------------	------	-------	-----	---	---

120 W
40 W

## **Product Datasheet**

## HED631H

Endurance	
Electric endurance in number of cycles	1000
Number of mechanical operations	4000
Equipment	
Number of auxiliary contacts as change-over contact	
Number of auxiliary contacts as normally closed contact	
Number of auxiliary contacts as normally open contact	(
Safety	
ngress Protection (IP) class	IP4>
Use conditions	
Operating temperature	-25 - 70 °C
Connection	
Cross-section flexible conductor	35 - 240 mm
Cross-section rigid conductor	35 - 240 mm
Connector/plug type	Termina
Controls and indicators	
Motor drive integrated	No
Compatibility	
Suitable for DIN Rail	No
Power supply	
Position power supply	Bidirectiona