

# Product Datasheet

## TRM692G



TRM692G



Module 1 flush mounted output 3A for shutters or blinds + 2 inputs, KNX radio

### Technical Features

#### Settings

Supported configuration mode [quicklink](#)

#### Connectivity

With bus system KNX radio Yes

#### Installation, mounting

Mounting on Flush mounting

#### Materials

Colour Light grey

#### Equipment

With switch for manual switch Yes

#### Electric current

Max. switching current 3 A

#### Use conditions

Operating temperature -10 - 50 °C

#### Connection

Cross-section flexible conductor 0.5 - 1.5 mm<sup>2</sup>

Cross-section rigid conductor 0.5 - 2.5 mm<sup>2</sup>

#### Capacity

Number of modules 0

#### Texts

Function Easy additional functions: +6 scenes  
Repeat function can be activated to increase the radio range  
Reset function (to factory setting)  
Type of connection With screw-in lift terminals

#### Sustainability

RoHS conform Yes