



TRM692G



Module 1 flush mounted output 3A for shutters or blinds + 2 inputs, KNX radio

Technical Features

Settings

Supported configuration mode quicklink

Connectivity

With bus system KNX radio Yes

Installation, mounting

Mounting on Flush mounting

Materials

Colour Light grey

Equipment

With switch for manual switch Yes

Electric current

Max. switching current 3 A

Use conditions

Operating temperature -10 - 50 °C

Connection

Cross-section flexible conductor 0.5 - 1.5 mm²

Cross-section rigid conductor 0.5 - 2.5 mm²

Capacity

Number of modules 0

Texts

Function Easy additional functions: +6 scenes
Repeat function can be activated to increase the radio range
Reset function (to factory setting)

Type of connection With screw-in lift terminals

Sustainability

RoHS conform Yes