



TRM692G



**1 FLUSH MOUNTED OUTPUT 3A FOR SHUTTERS OR BLINDS + 2 INPUTS KNX RF**

**Technical Features**

**Settings**

Supported configuration mode quiclink

**Connectivity**

With bus system KNX radio Yes

**Installation, mounting**

Mounting on Flush mounting

**Materials**

Colour Light grey

**Equipment**

With switch for manual switch Yes

**Electric current**

Max. switching current 3 A

**Use conditions**

Operating temperature -10 - 50 °C

**Connection**

Cross-section flexible conductor 0.5 - 1.5 mm<sup>2</sup>

Cross-section rigid conductor 0.5 - 2.5 mm<sup>2</sup>

**Capacity**

Number of modules 0

**Texts**

Function Easy additional functions: +6 scenes  
Repeat function can be activated to increase the radio range  
Reset function (to factory setting)

Type of connection With screw-in lift terminals