



85745226



KNX radio timer quicklink, display, Q.x, ant. velvety, lacq.

Technical Features

Settings

Supported configuration mode quicklink

Connectivity

With bus system KNX radio Yes

Radio protocol KNX Radio

Equipment

Number of channels 1

Scope of delivery

Bus connection included Yes

Equipment

Summer-/wintertime switchover Yes

Functions

Astro time shift 2 h

Battery backup 8 h

Power reserve in years 0 y

Use conditions

Operating temperature -5 - 45 °C

Materials

Colour Anthracite

Texts

Function Easy additional functions: +6 scenes, dimming, 1 up/down button control, priority
Configurable transmission and/or reception behaviour
With keylock
Party function, no execution of automatic, radio and extension unit commands (switch protection)
Reset function (to factory setting)

Protection With dismantling protection

Capacity

Number of modules 0

Dimensions

Height 58.40 mm

Width 58.40 mm

Depth 30 mm

Suitable for

Q.x