

85745226









△‱

KNX radio timer quicklink, display, Q.x, ant. velvety, lacq.

Technical Features	
Settings	
Supported configuration mode	quicklink
Connectivity	
With bus system KNX radio	Yes
Radio protocol	KNX Radio
Equipment	
Number of channels	1
Scope of delivery	
Bus connection included	Yes
Equipment	
Summer-/wintertime switchover	Yes
Functions	
Astro time shift	2 h
Battery backup	8 h
Power reserve in years	0 у
Use conditions	
Operating temperature	-5 - 45 °C
Materials	
Colour	Anthracite

ite **Texts**

Function Easy additional functions: +6 scenes, dimming, 1 up/down button control, priority
Configurable transmission and/or reception behaviour With keylock

Party function, no execution of automatic, radio and extension unit commands (switch protection) Reset function (to factory setting)

Protection With dismantling protection

Number of modules

Capacity

Dimensions Height 58.40 mm Width 58.40 mm 30 mm Depth

Suitable for

Q.x

0