



85745285



### KNX radio timer quicklink, display, S.1/B.3/B.7, ant., matt

#### Technical Features

##### Settings

|                              |           |
|------------------------------|-----------|
| Supported configuration mode | quicklink |
|------------------------------|-----------|

##### Connectivity

|                           |           |
|---------------------------|-----------|
| With bus system KNX radio | Yes       |
| Radio protocol            | KNX Radio |

##### Equipment

|                    |   |
|--------------------|---|
| Number of channels | 1 |
|--------------------|---|

##### Scope of delivery

|                         |     |
|-------------------------|-----|
| Bus connection included | Yes |
|-------------------------|-----|

##### Equipment

|                               |     |
|-------------------------------|-----|
| Summer-/wintertime switchover | Yes |
|-------------------------------|-----|

##### Functions

|                        |     |
|------------------------|-----|
| Astro time shift       | 2 h |
| Battery backup         | 8 h |
| Power reserve in years | 0 y |

##### Use conditions

|                       |            |
|-----------------------|------------|
| Operating temperature | -5 - 45 °C |
|-----------------------|------------|

##### Materials

|        |            |
|--------|------------|
| Colour | Anthracite |
|--------|------------|

##### Texts

|            |                                                                                                                                                                                                                                                                                                      |
|------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Function   | Easy additional functions: +6 scenes, dimming, 1 up/down button control, priority<br>Configurable transmission and/or reception behaviour<br>With keylock<br>Party function, no execution of automatic, radio and extension unit commands (switch protection)<br>Reset function (to factory setting) |
| Protection | With dismantling protection                                                                                                                                                                                                                                                                          |

##### Capacity

|                   |   |
|-------------------|---|
| Number of modules | 0 |
|-------------------|---|

##### Dimensions

|        |          |
|--------|----------|
| Height | 55.50 mm |
| Width  | 55.50 mm |
| Depth  | 30.30 mm |

##### Suitable for

|         |  |
|---------|--|
| S.x/B.x |  |
|---------|--|

##### Sustainability

|              |     |
|--------------|-----|
| RoHS conform | Yes |
|--------------|-----|