



85745177



KNX radio blind time switch quicklink, display, K.5, al., matt, lacq.

Technical Features

Settings

Supported configuration mode	quicklink
------------------------------	-----------

Connectivity

With bus system KNX radio	Yes
---------------------------	-----

Radio protocol	KNX Radio
----------------	-----------

Equipment

Number of channels	2
--------------------	---

Scope of delivery

Bus connection included	Yes
-------------------------	-----

Equipment

Summer-/wintertime switchover	Yes
-------------------------------	-----

Functions

Runtime	2 min
---------	-------

Astro time shift	2 h
------------------	-----

Battery backup	8 h
----------------	-----

Power reserve in years	0 y
------------------------	-----

Use conditions

Operating temperature	-5 - 45 °C
-----------------------	------------

Materials

Colour	Aluminium
--------	-----------

Texts

Function	Easy additional functions: +6 scenes, 1 up/down operating mode Configurable transmission and/or reception behaviour With keylock Party function, no execution of automatic, radio and extension unit commands (lock-out protection) Reset function (to factory setting)
Protection	With dismantling protection

Capacity

Number of modules	0
-------------------	---

Dimensions

Height	55 mm
--------	-------

Width	70 mm
-------	-------

Depth	30 mm
-------	-------

Suitable for

K.x	
-----	--

Sustainability

RoHS conform	Yes
--------------	-----