



85648126



**KNX radio button 4gang quicklink, Q.x, ant. velvety, lacq.**

**Technical Features**

**Connectivity**

With bus system KNX radio Yes

**Equipment**

Number of channels 4

Transmitter duty cycle 1 %

**Connectivity**

Receiver category 2

**Use conditions**

Operating temperature -5 - 45 °C

**Materials**

Colour Anthracite

**Texts**

Function Functions for the push-button operation areas up/down or left/right can be freely configured as receiver for controlling the connected load and as transmitter for remote control of a blind, for example  
Configurable transmission and/or reception behaviour  
Reset function (to factory setting)

Protection With dismantling protection

**Sustainability**

RoHS conform Yes