:hager

85648126

KNX radio button 4gang quicklink, Q.x, ant. velvety, lacq.

Technical Features

Connectivity

With bus system KNX radio	Yes

Equipment

Number of channels	4
Transmitter duty cycle	1 %

Connectivity

Receiver category	2

Use conditions

Operating temperature	-5 - 45 ℃

Materials

Colour	Anthracite

Texts

Function	Functions for the push-button operation areas up/down or left/right can be freely configured as receiver for controlling the connected load and as transmitter for remote control of a blind, for example Configurable transmission and/or reception behaviour Reset function (to factory setting)
Protection	With dismantling protection

Sustainability

RoHS conform	Yes