



TRM692G



Module 1 flush mounted output 3A for shutters or blinds + 2 inputs, KNX radio

Technical Features

Settings

Supported configuration mode	quicklink
------------------------------	-----------

Connectivity

With bus system KNX radio	Yes
---------------------------	-----

Installation, mounting

Mounting on	Flush mounting
-------------	----------------

Materials

Colour	Light grey
--------	------------

Equipment

With switch for manual switch	Yes
-------------------------------	-----

Electric current

Max. switching current	3 A
------------------------	-----

Use conditions

Operating temperature	-10 - 50 °C
-----------------------	-------------

Connection

Cross-section flexible conductor	0.5 - 1.5 mm²
Cross-section rigid conductor	0.5 - 2.5 mm²

Capacity

Number of modules	0
-------------------	---

Texts

Function	Easy additional functions: +6 scenes Repeat function can be activated to increase the radio range Reset function (to factory setting)
Type of connection	With screw-in lift terminals

Sustainability

RoHS conform	Yes
--------------	-----