



## TRM694G









## Module 1 FM output 4A free of potential + 2 inputs mains powered, KNX radio

Technical Features	
Connectivity	
Radio protocol	KNX Radio
Settings	
Supported configuration mode	ETS
	easy
	quicklink
Connectivity	
Receiver category	2
With his evetom KNY	No

Receiver category	2
With bus system KNX	No
With bus system KNX radio	Yes
Dimensions	
Dimensions	40 x 40 mm
Height	40 mm
Width	40 mm
Depth	20 mm
Built-in depth	40 mm
Electric current	
Rated current	4 A
Materials	
Colour	Light grey
Equipment	
Radio frequency bidirectional	Yes
With switch for manual switch	Yes
Frequency	
Frequency	50 - 50 Hz
Radio reception frequency	868.30 - 868.30 MHz

Electric current	
Rated current	4 A
Materials	
Colour	Light grey
Equipment	
Radio frequency bidirectional	Yes
With switch for manual switch	Yes
Frequency	
Frequency	50 - 50 Hz
Radio reception frequency	868.30 - 868.30 MHz
Power	
Output power	920 W
230 V incandescent and halogen lamp	600 W
Voltage	
Operating voltage	230 - 230 V
Rated operational voltage Ue	230 - 230 V
System supply voltage	230 V AC
Safety	
Ingress Protection (IP) class	IP20
Use conditions	
Operating temperature	-10 - 50 °C

Use conditions Operating temperature	-10 - 50 °C
Connection	
Cross-section rigid conductor	0.5 - 2.5 mm <sup>2</sup>
Cross-section flexible conductor	0.5 - 1.5 mm <sup>2</sup>
Texts	
Function	Easy additional functions: +6 scenes Repeat function can be activated to increase the radio range Reset function (to factory setting)

Installation mode

Type of connection

For installation behind flush-mounted inserts

With screw-in lift terminals

## **Product Datasheet**

TRM694G



Sustainability
RoHS conform
Yes