## **Product Datasheet** WXT501





WXT501













## Movement detector 180°, KNX, module, 1,10m

#### **Technical Features**

-		
I lum	ensions	
	CHOIDHS	

Differisions	
Recommended installation height	1.10 - 1.10 m
Settings	
Supported configuration mode	ETS
	easy
Minimal duty cycle	10 s

#### **Functions**

Maximal duty cycle	30 min

## Connectivity

With bus system KNX radio	No

#### Voltage

Operating voltage over bus	21 - 32 V

# Scope of delivery

Bus connection included	Yes
-------------------------	-----

#### Electric current

Bus current consumption data transfer	10 mA

## Lighting

Response brightness adjustable 5 - 1	1000 lx
--------------------------------------	---------

#### Detection

Detection angle adjustable	45 - 90 °
Detection angle horizontal	90 - 180

### Use conditions

Operating temperature	-5 - 45 °C

## Materials

Material	Thormonlactio

## **Texts**

Push button	With button for automatic/permanent ON/permanent OFF
Operating mode	With test mode
	Master/slave operation for covering large detection areas
	With 3 operating modes: automatic/permanent ON/permanent
	OFF

Function	Presence simulation
	With party function

#### Sustainability

RoH	nform Yes	ŝ