



TR131N

**Media coupler, white, KNX**

**Technical Features**

**Voltage**

Operating voltage over bus 30 - 30 V

**Connectivity**

Radio protocol KNX Radio

**Settings**

Supported configuration mode ETS  
easy  
quicklink

**Power**

Current consumption 4 mA

**Safety**

Ingress Protection (IP) class IP30

**Frequency**

Frequency 868300000 - 868300000 Hz

**Use conditions**

Operating temperature 0 - 45 °C

**Controls and indicators**

With LED indication Yes

**Connection**

Connector/plug type Bus system Connection terminal

Connector/plug type Push button/switch

**Sustainability**

RoHS conform Yes