



1.71M

## Fuse-switch-disconnector D02 E18 63A AC400 V 1pole DIN rail

## **Technical Features**

lechnical Features	
Fuse	
Fuse size	D02
Architecture	
Number of poles	
Electric current	00.4
Rated current	63 A
Rated current of fuse cartridge	2 A 4 A
	6 A
	10 A 16 A
	20 A
	25 A
	32 A
	35 A 40 A
	50 A
	63 A
Installation, mounting	
Mounting on	DIN rail
Nominal tightening torque	3.30 - 3.30 Nm
Dimensions	
Height	85 mm
Width	27 mm
Depth	79 mm
Берит	70 11111
Connection	
Cross-section flexible conductor	1.5 - 35 mm <sup>2</sup>
Use conditions	
Operating temperature	-25 - 40 °C
Frequency	FO FOUL
Frequency	50 - 50 Hz
Power	
Total power loss under IN	1.60 W
Connection	
Cross-section rigid conductor	1.5 - 35 mm <sup>2</sup>
Power	F F0.W
Power loss of the Fuse-Link installed in device	5.50 W
Texts	
Protection	Contact protection safe from touch by finger and back of
	hand
Electric current	
Rated conditional short-circuit current lcc	50 kA
Voltage	
Voltage Rated insulation voltage Ui	800 V
Tated insulation voltage of	800 V
Safety	
Ingress Protection (IP) class	IP20C
Materials	
Material	Plastic
	T lastic

## **Product Datasheet**





## Sustainability

Halogen free	Yes
REACh-SVHC free	Yes
RoHS conform	Yes